


Solutions for handling control

+39 039 99.11.011



PF090303000120

Home Page | [Print](#)



IP 65 **CE** **ERC**

Revolution ratio

1:300 1:300

Cable clamp 1
Cable clamp 2
Cable clamp 3

PRPS0064PE

Notes

Shaft

Code PRT00107PE

End side Front
Length (L) 43,00 mm
Flexible No
Standard diameter 12 mm
End type Radial hole
Dimension A 4,00 mm
Dimension B 7,00 mm




Plate PRSL9297PI

Cover PRSL5582PI

Base PRSL5042PI

Pinion gear PRSL0919PI

Cam set Code: FCL40026

	Cams	Switches
4		PRSL7194PI PRSL0110XX
3 (60°)		PRSL7195PI PRSL0110XX
2 (60°)		PRSL7195PI PRSL0110XX
1		PRSL7194PI PRSL0110XX

Note: cams numbering is bottom up

Potentiometer / encoder 2 PA01AA01

Anti condensation option

This configuration has been saved in our records and will be valid 180 days from the date of creation. After that date it will be deleted.
The image is representative and does not match the actual product.

For more information on this product or to get a quote contact us

TER Tecno Elettrica Ravasi srl

Sede Operativa / Headquarter

Via Garibaldi 29/31
23885 Calco (LC) - Italy
Tel. +39 039 99.11.011
Fax +39 039 99.10.445
E-mail info@terworld.com

Sede Legale / Registered Office

Via San Vigilio 2 - 23887 Olgiate Molgora (LC) - Italy
Capitale sociale / Capital stock € 150.000
R.E.A Lecco N. 136104 - M.I.C. 001225
Registro Imprese di Lecco / Business register in Lecco
C.F.P.IVA / Fiscal Code/VAT no. 00222410136
PEC tecnoelettricaravasi@pec.edslegal.it

"Do you want receive TER news updates?"

[Subscribe to our newsletter](#)

[Term of privacy](#)



© 2012 TER Tecno Elettrica Ravasi srl

